



This Quick Reference Guide includes short descriptions on how to use the basic functions. To learn more about all available functions, please see the related User Guide.

### Switching On/Off

Switch on: (until the display lights up) PIN code. (if requested)

Switch off: (until blank display)

### Answer Calls

Answer: or (Handsfree)

Switch off ringer:

End call:

### Make Calls

Dialling while "on-hook": Enter number

Dialling while "off-hook": (Hold for more than one second) Enter number

From Phone book: (PhoneBook)  
 (Find&Call)   
 Enter letter   
 Select name

From Call List (if available): Select name

### When You Receive a Busy Tone

Automatic Call-back (Busy extension): **6** Go "off hook" when called back  
 France, Finland, Sweden: **5**

Cancel specific Call-back: **# 3 7 \*** Ext. no. #

Cancel all Call-backs: **# 3 7 #**

Call Waiting: **5** (Stay "off hook")  
 France, Finland: **6**  
 Sweden: **4**

Cordless Phone for MD110 Communication System

## Quick Reference Guide

The complete User Guide is available in electronic format for online viewing or printout on <http://www.ericsson.com/enterprise>

### During Calls

Activate/deactivate

Handsfree:

Inquiry: Ongoing conversation

Call 3rd party

Refer Back from Inquiry: **2**

Transfer: *Make Inquiry*  
 (Before or after answer)

Conference: *Make Inquiry*  
**3** (To establish)  
 (To leave)

### Call Forwarding

Internal Follow-me: **\* 2 1 \*** New no. #   
 U.K.: **\* 2 \***

Cancel: **# 2 1 #**   
 U.K.: **# 2 #**

External Follow-me: **\* 2 2 #** Line access code  
 External no. #

Cancel: **# 2 2 #**

Personal Number: \* **\* 1 0 \*** (1-5) #

Cancel: **# 1 0 #**

Bypass Diversion: **\* 6 0 \*** Ext. no. #

### Free Seating \*

Log on: **\* 1 1 \***  
 Authorization code \*  
 Own ext. no. #

Log off: **# 1 1 #**

Notes: Ext. no. = Extension number  
 \* Optional

### Menu Structure

#### Options available when "on-hook"

##### PhoneBook

Find&Call \*

Store

Find&Edit \*

DeleteAll \*

##### Messages x \*

Voice: x Mailbox

AddNew

AddCallList

Edit

Delete

##### Settings

Alarm

AutoKeyLock

Alerts

PhoneLock

MasterReset

Language

MessageKey

Display

SetAlarm

AlarmOff \*

RingVolume

RingType

KeySound

DiscreetRng

Vibrator

PowerOn

Subscript

ChangePIN

Mess.KeyNo

Light

Contrast

##### Networks \*\*

SelectNet

Priority \*

Rename

Delete

Subscribe

Internal

External

CallBack

Message

OnIfSilent

On

Off

##### Information

CallList \*

MissedCalls \*

LastCall \*

TotalCalls

ShowIPEI

DevServices \*

- Move within a menu.
- Make selection. Move to submenu.
- Move to previous menu.
- Move to idle display.

#### Options available when "off-hook"

Find&Call \*

CallList \*

GoToDTMF \*\*\*

DevServices \*

#### Notes:

\* Available under certain conditions (e.g. entries stored).

\*\* Only to be used by system administrator

\*\*\* Alternative menu DTMF-Long is not applicable for MD110.

### Write Text

Useful when searching for, and adding or editing, a name in the Phone book. Press a digit key repeatedly (example: press key **5** three times to get the character "L")

Insert a space: **1**

Erase an entry:

Move in text, left/right:

Upper/lower case: \*

Insert dial tone pause: \* Hold for more than one second

To confirm your edit and exit the menu:

### Messages \*

Check messages: A message icon appears

### Absence Information \*

Order (For own extension): **\* 2 3 \*** Absence code \*  
 Date/Time #

Cancel: **# 2 3 #**

### Volume Control

Earpiece volume: (During a call)

Turn ringer Off/On:  
 For current call: (When ringing)  
 Permanently: (When not ringing)

Warning: The phone may retain small magnetic articles around the earpiece region.